

Three-Party Entanglement in Tripartite Teleportation Scheme through Noisy Channels

Eylee Jung, Mi-Ra Hwang, DaeKil Park

Department of Physics, Kyungnam University, Masan, 631-701, Korea

Sayatnova Tamaryan

Theory Department, Yerevan Physics Institute, Yerevan-36, 375036, Armenia

Abstract

In this paper we have tried to interpret the physical role of the three-tangle and π -tangle in the real physical information process. For the model calculation we adopt the three-party teleportation scheme through the various noisy channels. The three parties consist of sender, accomplice and receiver. It is shown that the π -tangles for the X- and Z-noisy channels vanish at $\kappa t \rightarrow \infty$ limit, where κt is a parameter introduced in the master equation of Lindblad form. In this limit the receiver's maximum fidelity reduces to the classical limit $2/3$. However, this nice feature is not maintained at the Y- and isotropy-noise channels. For Y-noise channel the π -tangle vanishes at $0.61 \leq \kappa t$. At $\kappa t = 0.61$ the receiver's maximum fidelity becomes 0.57, which is much less than the classical limit. Similar phenomenon occurs at the isotropic noise channel. We also computed the three-tangles analytically for the X- and Z-noise channels. The remarkable fact is that the three-tangle for Z-noise channel is exactly same with the corresponding π -tangle. In the X-noise channel the three-tangle vanishes at $0.10 \leq \kappa t$. At $\kappa t = 0.10$ the receiver's fidelity can be reduced to the classical limit provided that the accomplice performs the measurement appropriately. However, the receiver's maximum fidelity becomes $8/9$, which is much larger than the classical limit. Since the Y- and isotropy-noise channels are rank-8 mixed states, their three-tangles are not computed explicitly in this paper. Instead, we have derived their upper bounds with use of the analytical three-tangles for other noisy channels. Our analysis strongly suggests that we need different three-party entanglement measure whose value is between three-tangle and π -tangle.

I. INTRODUCTION

It is well-known that Entanglement of quantum state is a valuable physical resource in quantum information theories[1]. It makes the quantum teleportation[2] and superdense coding[3] possible within the quantum mechanical law. Furthermore, it is the physical resource which is responsible for the speed-up of the quantum computer[4]. In this reason there has been a flurry of activity recently in the research of entanglement.

Many new properties for the entanglement of three- or higher-qubit pure states have been reported in the recent papers[5]. However, it is in general much more difficult to understand the properties of entanglement for the mixed states except bipartite case. These difficulties are mainly originated from the fact that the mixed state entanglement is defined by a convex-roof extension[6, 7] of the pure state entanglement. In order to compute the entanglement defined by convex-roof method one should derive the optimal decomposition for the given mixed state. Generally, however, it is highly non-trivial task to derive the optimal decomposition for the arbitrary mixed states. This computational difficulty makes it difficult to characterize the multipartite entanglement for the mixed states.

For the bipartite qubit states, fortunately, Wootters found how to derive the optimal decomposition for the concurrence, entanglement measure for the bipartite states, in Ref.[8, 9]. Thus, one can compute the concurrence $\mathcal{C}(\rho)$ for the arbitrary mixed states ρ by Wootters formula

$$\mathcal{C}(\rho) = \max(0, \lambda_1 - \lambda_2 - \lambda_3 - \lambda_4) \quad (1.1)$$

where λ_i 's are the eigenvalues, in decreasing order, of the Hermitian matrix

$$\sqrt{\sqrt{\rho}(\sigma_y \otimes \sigma_y)\rho^*(\sigma_y \otimes \sigma_y)\sqrt{\rho}}.$$

Complete understanding on the bipartite concurrence makes it possible to derive the purely three-party entanglement, called three-tangle, for the three-qubit pure states[10]. This arises from the observation that the three-qubit pure state $|\psi_{ABC}\rangle$ satisfies the following inequality

$$\mathcal{C}_{AB}^2 + \mathcal{C}_{AC}^2 \leq \mathcal{C}_{A(BC)}^2 \quad (1.2)$$

where $\mathcal{C}_{AB}$ and $\mathcal{C}_{AC}$ are concurrences for the reduced states $\rho^{AB} = \text{Tr}_C|\psi_{ABC}\rangle\langle\psi_{ABC}|$ and $\rho^{AC} = \text{Tr}_B|\psi_{ABC}\rangle\langle\psi_{ABC}|$, and $\mathcal{C}_{A(BC)}$ is a concurrence between a pair BC and A . Therefore, $\mathcal{C}_{A(BC)}$ represents an total entanglement of the qubit A arising due to the remaining qubits.

For pure state $\mathcal{C}_{A(BC)}^2$ reduces to $4\det\rho^A$, where $\rho^A = \text{Tr}_{BC}|\psi_{ABC}\rangle\langle\psi_{ABC}|$ and is called one-tangle. In this sense, the inequality (1.2) indicates that the total one-tangle is greater than sum of two-tangles. In addition, this observation naturally implies that $\tau_{ABC} \equiv \mathcal{C}_{A(BC)}^2 - (\mathcal{C}_{AB}^2 + \mathcal{C}_{AC}^2)$, which is called three-tangle, represents the purely three-way entanglement. For three-qubit pure state $|\psi\rangle = \sum_{i,j,k=0}^1 a_{ijk}|ijk\rangle$, the three-tangle τ_{ABC} becomes[10]

$$\tau_{ABC} = 4|d_1 - 2d_2 + 4d_3|, \quad (1.3)$$

where

$$\begin{aligned} d_1 &= a_{000}^2 a_{111}^2 + a_{001}^2 a_{110}^2 + a_{010}^2 a_{101}^2 + a_{100}^2 a_{011}^2 \\ d_2 &= a_{000} a_{111} a_{011} a_{100} + a_{000} a_{111} a_{101} a_{010} + a_{000} a_{111} a_{110} a_{001} \\ &\quad + a_{011} a_{100} a_{101} a_{010} + a_{011} a_{100} a_{110} a_{001} + a_{101} a_{010} a_{110} a_{001} \\ d_3 &= a_{000} a_{110} a_{101} a_{011} + a_{111} a_{001} a_{010} a_{100}. \end{aligned} \quad (1.4)$$

The three-tangle defined by Eq.(1.3) exactly coincides with the modulus of a Cayley's hyperdeterminant[11, 12] and is an invariant quantity under the local $SL(2, \mathbb{C})$ transformation[13, 14].

The three-tangle (1.3) has following two important properties. Firstly, for a completely separable ($A - B - C$) and biseparable ($A - BC$, $B - AC$, $AB - C$) states τ_{ABC} becomes zero. This means that the three-tangle is truly the pure three-party quantity related to the entanglement. Secondly, the three-tangles for the Greenberger-Horne-Zeilinger(GHZ)[15] and W[16] states defined

$$|GHZ\rangle = \frac{1}{\sqrt{2}}(|000\rangle + |111\rangle) \quad |W\rangle = \frac{1}{\sqrt{3}}(|001\rangle + |010\rangle + |100\rangle) \quad (1.5)$$

become

$$\tau_{ABC}(|GHZ\rangle) = 1 \quad \tau_{ABC}(|W\rangle) = 0. \quad (1.6)$$

Since the whole three-qubit pure states can be classified by completely separable, biseparable, GHZ-type, and W-type states through stochastic local operation and classical communication(SLOCC)[16], Eq.(1.5) indicates that the three-tangle does not properly reflect the three-party entanglement of the W-type states.

For the mixed states the three-tangle is defined by a convex-roof method[6, 7] as follows:

$$\tau_{ABC}(\rho) = \min \sum_i p_i \tau_{ABC}(\rho_i) \quad (1.7)$$

where the minimum is taken over all possible ensembles of pure states. The pure state ensemble corresponding to the minimum τ_{ABC} is called optimal decomposition. It is in general highly difficult to derive the optimal decomposition for the arbitrary mixed states. Fortunately, Lohmayer et al[17] have derived recently the optimal decomposition when the mixed state ρ is

$$\rho(p) = p|GHZ\rangle\langle GHZ| + (1-p)|W\rangle\langle W| \quad (1.8)$$

and have computed the three-tangle explicitly. They also have found that the Coffman-Kundu-Wootters(CKW) inequality (1.2) holds for mixed states as well as pure states. Subsequently, the three-tangle for the rank-2 mixed state composed of the generalized GHZ and generalized W states has been computed in Ref.[18]. In Ref.[19] furthermore, the optimal decompositions and the three-tangle for the rank-3 mixed state composed of GHZ, W, and flipped W states are also explicitly derived. Most recently, the three-tangle for the rank-4 mixed states composed of 4-different GHZ states are explicitly computed in Ref.[20].

On the other hand, in order to reflect the three-party entanglement of the W-type states properly we need to define new three-party entanglement measure different from the three-tangle. One of the candidate is a π -tangle discussed in Ref.[21]. The π -tangle is defined in terms of the global negativities[22] defined

$$\mathcal{N}^A = ||\rho^{T_A}|| - 1 \quad \mathcal{N}^B = ||\rho^{T_B}|| - 1 \quad \mathcal{N}^C = ||\rho^{T_C}|| - 1 \quad (1.9)$$

where $||R|| = \text{Tr}\sqrt{RR^\dagger}$, and the superscripts T_A , T_B and T_C represent the partial transpositions for the A -qubit, B -qubit and C -qubit respectively. Due to the separability criterion via partial transposition[23, 24, 25] it is easy to show that the global negativities vanish for the separable states. It is worthwhile noting that the computation of the global negativities is relatively simple compared to concurrence or three-tangle for the mixed states since it does not need the convex-roof extension. In addition, the negativities also satisfy the monogamy inequality

$$\mathcal{N}_{AB}^2 + \mathcal{N}_{AC}^2 \leq \mathcal{N}_{A(BC)}^2 \quad (1.10)$$

like concurrence. Then, the π -tangle is defined as

$$\pi_{ABC} = \frac{1}{3}(\pi_A + \pi_B + \pi_C) \quad (1.11)$$

where

$$\pi_A = \mathcal{N}_{A(BC)}^2 - (\mathcal{N}_{AB}^2 + \mathcal{N}_{AC}^2) \quad \pi_B = \mathcal{N}_{B(AC)}^2 - (\mathcal{N}_{AB}^2 + \mathcal{N}_{BC}^2) \quad \pi_C = \mathcal{N}_{(AB)C}^2 - (\mathcal{N}_{AC}^2 + \mathcal{N}_{BC}^2). \quad (1.12)$$

It is easy to show that the π -tangles for $|GHZ\rangle$ and $|W\rangle$ become

$$\pi_{ABC}(|GHZ\rangle) = 1 \quad \pi_{ABC}(|W\rangle) = \frac{4}{9}(\sqrt{5} - 1) \sim 0.55. \quad (1.13)$$

Thus the π -tangle reflects the three-party entanglement of the W-type states unlike the three-tangle.

In this paper we would like to explore the physical role of the three-party entanglement in the real quantum information process. In order to discuss this issue we adopt the tripartite teleportation scheme discussed in Ref.[26]. Similar issue was discussed in Ref.[27], where the physical role of the concurrence is discussed in the bipartite teleportation through noisy channels. Ref.[27] has shown that the concurrences of the mixed state quantum channels arising due to some noises vanish in the region of $\bar{F} \leq 2/3$, where $\bar{F}$ is an average fidelity between initial Alice's unknown state and final Bob's state. Since $\bar{F} = 2/3$ corresponds to the best possible score when Alice and Bob communicate with each other through the classical channel[28], this result indicates that the entanglement of the quantum channel is a genuine physical resource for the teleportation process.

This paper is organized as follows. In section II we re-formulate the tripartite teleportation process[26] in terms of the density matrix. This re-description allows us to formulate the tripartite teleportation process when quantum channel is mixed state. The several basic quantities are calculated in this section, which are essential for the calculation of various fidelities in next sections. In section III we compute the accomplice's fidelities and receiver's fidelities when the tripartite teleportation process is performed through noisy channels. In section IV we compute the π -tangles for the various noisy channels. It is shown that the π -tangles for all noise channels decrease with increasing the decoherence parameter κt . This is in fact expected due to the fact that the decoherence in general disentangles the entanglement of quantum states like "sudden death". The π -tangle for X- and Z-noise channels vanish at the $\kappa t \rightarrow \infty$ limit. However, the π -tangles for Y- and isotropy-noise channels are found to be non-zero at the finite range of κt . In section V we compute the three-tangles for the X- and Z-noise channels. It is shown that the three-tangle for the Z-noise channel is exactly same with the corresponding π -tangle. The three-tangle for the X-noise channel

is shown to have three different expressions depending on the range of κt . Since the channels for the Y- and isotropy-noises are rank-8 mixed states, there is no general method to compute the three-tangles. However, we derived the upper bound of these three-tangles. In section VI we analyze the π -tangle and three-tangle by making use of the receiver's fidelities. The π -tangle seems to be too large to have a nice physical interpretation. The three-tangle also seems to be too small by similar manner. This analysis strongly suggests that we may need different three-party entanglement measure whose value is between three-tangle and π -tangle.

II. BASIC QUANTITIES

In this section we want to re-formulate the tripartite teleportation scheme in terms of the density matrices[29]. It involves sender (Alice), accomplice (Bob) and receiver (Charlie). Initially they share each single qubit of the GHZ state, *i.e.* $\rho_{GHZ} = |GHZ\rangle_{234}\langle GHZ|$. The purpose of the tripartite teleportation is as follows. Firstly, Alice at location 2 should transport a single qubit state

$$\rho_{in} = |\psi_{in}\rangle\langle\psi_{in}| \quad |\psi_{in}\rangle = \cos\left(\frac{\theta}{2}\right)e^{i\phi/2}|0\rangle + \sin\left(\frac{\theta}{2}\right)e^{-i\phi/2}|1\rangle \quad (2.1)$$

to the receiver, Charlie, at location 4 with fidelity $\bar{F}_C$ as high as possible with the help of the accomplice, Bob, at location 3. At the second time Alice should transport ρ_{in} to the accomplice, Bob, with fidelity $\bar{F}_B$ as high as possible. Of course, we cannot make $\bar{F}_B = \bar{F}_C = 1$ due to no-cloning/broadcast theorems[30, 31]. The task is accomplished if one can make $\bar{F}_B$ and $\bar{F}_C$ as high as possible. In this sense the tripartite teleportation scheme is similar to a quantum copier (cloning device)[32, 33, 34, 35].

From the postulate of quantum mechanics on composite systems the initial state of the tripartite teleportation process should be

$$\rho_{in} \otimes \rho_{GHZ}. \quad (2.2)$$

As will be discussed below ρ_{GHZ} will be changed into $\varepsilon(\rho_{GHZ})$ when noise is introduced when Alice, Bob and Charlie prepare the GHZ state initially, where ε is a quantum operation[1].

At the next stage Alice performs a projective measurement by preparing a set of the measurement operators $\{M_1, M_2, M_3, M_4\}$ with

$$M_1 = |\Phi^+\rangle\langle\Phi^+| \quad M_2 = |\Phi^-\rangle\langle\Phi^-| \quad M_3 = |\Psi^+\rangle\langle\Psi^+| \quad M_4 = |\Psi^-\rangle\langle\Psi^-|, \quad (2.3)$$

where

$$|\Phi^\pm\rangle = \frac{1}{\sqrt{2}}(|00\rangle \pm |11\rangle)_{12} \quad |\Psi^\pm\rangle = \frac{1}{\sqrt{2}}(|01\rangle \pm |10\rangle)_{12}. \quad (2.4)$$

Since $|\Phi^\pm\rangle$ and $|\Psi^\pm\rangle$ form a Bell basis, the operators satisfy the completeness constraint

$$\sum_m M_m^\dagger M_m = I. \quad (2.5)$$

From the quantum mechanical postulates the probability P_m , probability that the result of the Alice's measurement is m , is given by

$$P_m = \text{Tr} [(M_m^\dagger M_m \otimes I_{34}) (\rho_{in} \otimes \rho_{GHZ})] \quad (2.6)$$

and the state of the system after the Alice's measurement reduces to

$$\tilde{\rho}_m = \frac{1}{P_m} (M_m \otimes I_{34}) (\rho_{in} \otimes \rho_{GHZ}) (M_m \otimes I_{34})^\dagger. \quad (2.7)$$

For our case we have $P_1 = P_2 = P_3 = P_4 = 1/4$. After measurement, Alice broadcasts her measurement outcome to Bob and Charlie via a classical channel.

Next, our concern is moved to the subsystem of Bob and Charlie. This process can be performed by tracing out the Alice's subsystem, *i.e*

$$\pi_{3,4}^m = \text{Tr}_{1,2} (\tilde{\rho}_m). \quad (2.8)$$

After then, the accomplice, Bob, performs a projective measurement again by preparing a set of measurement operators $\{N_1, N_2\}$ with

$$N_1 = |\mu^+\rangle\langle\mu^+| \quad N_2 = |\mu^-\rangle\langle\mu^-|, \quad (2.9)$$

where

$$|\mu^+\rangle = \sin \nu |0\rangle + \cos \nu |1\rangle \quad |\mu^-\rangle = \cos \nu |0\rangle - \sin \nu |1\rangle. \quad (2.10)$$

Since $|\mu^+\rangle$ and $|\mu^-\rangle$ form a basis for the Bob's qubit, the completeness condition

$$N_1^\dagger N_1 + N_2^\dagger N_2 = I \quad (2.11)$$

is naturally satisfied. From the quantum mechanical postulates again the probability q_{mn} , probability that the result of the Bob's measurement is n on condition that the outcome of Alice's measurement is m , reduces to

$$q_{mn} = \text{Tr} [(N_n \otimes I_4) \pi_{3,4}^m] \quad (2.12)$$

and the state of the system after the Bob's measurement becomes

$$\tilde{\pi}_{mn} = \frac{1}{q_{mn}} (N_n \otimes I_4) \pi_{3,4}^m (N_n \otimes I_4)^\dagger. \quad (2.13)$$

For our case q_{mn} becomes

$$q_{11} = q_{21} = q_{32} = q_{42} = \frac{1}{2} (1 - \cos 2\nu \cos \theta) \quad q_{12} = q_{22} = q_{31} = q_{41} = \frac{1}{2} (1 + \cos 2\nu \cos \theta). \quad (2.14)$$

After then, our concern is moved to the subsystem of Charlie by tracing out the Bob's subsystem, *i.e.*

$$\chi_4^{mn} = \text{Tr}_3 (\tilde{\pi}_{mn}). \quad (2.15)$$

Finally, Charlie takes an appropriate unitary transformation to his own qubit

$$\tau_{mn} = u_4^{mn} \chi_4^{mn} (u_4^{mn})^\dagger. \quad (2.16)$$

The unitary operator u_4^{mn} becomes

$$u_4^{11} = u_4^{22} = I \quad u_4^{12} = u_4^{21} = \sigma_z \quad u_4^{31} = u_4^{42} = \sigma_x \quad u_4^{32} = u_4^{41} = \sigma_y \quad (2.17)$$

where σ_i is usual Pauli matrices. At this stage the tripartite teleportation process is terminated.

Now, we want to discuss the tripartite teleportation process through a noisy channel. If noise is introduced at the initial stage when Alice, Bob, and Charlie share their each single qubit of $|GHZ\rangle$, ρ_{GHZ} is, in general, changed into the mixed state. The mixed state can be derived by solving a master equation in the Lindblad form[36]

$$\frac{\partial \rho}{\partial t} = -i[H_S, \rho] + \sum_{i,\alpha} \left(L_{i,\alpha} \rho L_{i,\alpha}^\dagger - \frac{1}{2} \{ L_{i,\alpha}^\dagger L_{i,\alpha}, \rho \} \right) \quad (2.18)$$

where the Lindblad operator $L_{i,\alpha} \equiv \sqrt{\kappa_{i,\alpha}} \sigma_\alpha^{(i)}$ acts on the i th qubit and describes decoherence. Of course, the operator $\sigma_\alpha^{(i)}$ denotes the Pauli matrix of the i th qubit with $\alpha = x, y, z$. The constant $\kappa_{i,\alpha}$ is approximately equal to the inverse of decoherence time. In this paper we will assume for simplicity that the constant $\kappa_{i,\alpha}$ is independent of i and α , *i.e.* $\kappa_{i,\alpha} = \kappa$.

Solutions of Eq.(2.18) for the $(L_{2,x}, L_{3,x}, L_{4,x})$, $(L_{2,y}, L_{3,y}, L_{4,y})$, $(L_{2,z}, L_{3,z}, L_{4,z})$, and isotropy noises were solved explicitly in Ref.[37]. The spectral decompositions of the re-

sults are as follows:

$$\begin{aligned}
\varepsilon_X(\rho_{GHZ}) &= x|GHZ, 1\rangle\langle GHZ, 1| + \frac{1-x}{3} \left[|GHZ, 3\rangle\langle GHZ, 3| \right. \\
&\quad \left. + |GHZ, 5\rangle\langle GHZ, 5| + |GHZ, 7\rangle\langle GHZ, 7| \right] \quad \left(x = \frac{1}{4}(1 + 3e^{-4\kappa t}) \right) \\
\varepsilon_Y(\rho_{GHZ}) &= \frac{y_+^3}{8}|GHZ, 1\rangle\langle GHZ, 1| + \frac{y_-^3}{8}|GHZ, 2\rangle\langle GHZ, 2| \\
&\quad + \frac{y_+ y_-^2}{8} \left[|GHZ, 3\rangle\langle GHZ, 3| + |GHZ, 5\rangle\langle GHZ, 5| + |GHZ, 7\rangle\langle GHZ, 7| \right] \\
&\quad + \frac{y_+^2 y_-}{8} \left[|GHZ, 4\rangle\langle GHZ, 4| + |GHZ, 6\rangle\langle GHZ, 6| + |GHZ, 8\rangle\langle GHZ, 8| \right] \\
&\quad (y_{\pm} = 1 \pm e^{-2\kappa t}) \\
\varepsilon_Z(\rho_{GHZ}) &= z|GHZ, 1\rangle\langle GHZ, 1| + (1-z)|GHZ, 2\rangle\langle GHZ, 2| \quad \left(z = \frac{1}{2}(1 + e^{-6\kappa t}) \right) \\
\varepsilon_I(\rho_{GHZ}) &= \frac{1+3p^2+4p^3}{8}|GHZ, 1\rangle\langle GHZ, 1| + \frac{1+3p^2-4p^3}{8}|GHZ, 2\rangle\langle GHZ, 2| \\
&\quad + \frac{1-p^2}{8} \left[I - (|000\rangle\langle 000| + |111\rangle\langle 111|) \right] \quad (p = e^{-4\kappa t})
\end{aligned} \tag{2.19}$$

where the subscripts X , Y , Z , and I represent the type of noise channels, and

$$\begin{aligned}
|GHZ, 1\rangle &= \frac{1}{\sqrt{2}}(|000\rangle + |111\rangle) & |GHZ, 2\rangle &= \frac{1}{\sqrt{2}}(|000\rangle - |111\rangle) \\
|GHZ, 3\rangle &= \frac{1}{\sqrt{2}}(|001\rangle + |110\rangle) & |GHZ, 4\rangle &= \frac{1}{\sqrt{2}}(|001\rangle - |110\rangle) \\
|GHZ, 5\rangle &= \frac{1}{\sqrt{2}}(|010\rangle + |101\rangle) & |GHZ, 6\rangle &= \frac{1}{\sqrt{2}}(|010\rangle - |101\rangle) \\
|GHZ, 7\rangle &= \frac{1}{\sqrt{2}}(|011\rangle + |100\rangle) & |GHZ, 8\rangle &= \frac{1}{\sqrt{2}}(|011\rangle - |100\rangle).
\end{aligned} \tag{2.20}$$

quantities	no noise and Z noise	X and Y noises	Isotropy noise
P_1, P_2, P_3, P_4	$\frac{1}{4}$	$\frac{1}{4}$	$\frac{1}{4}$
$q_{11}, q_{21}, q_{32}, q_{42}$	$\frac{1}{2}(1 - \cos 2\nu \cos \theta)$	$\frac{1}{2}(1 - \cos 2\nu \cos \theta e^{-4\kappa t})$	$\frac{1}{2}(1 - \cos 2\nu \cos \theta e^{-8\kappa t})$
$q_{31}, q_{41}, q_{12}, q_{22}$	$\frac{1}{2}(1 + \cos 2\nu \cos \theta)$	$\frac{1}{2}(1 + \cos 2\nu \cos \theta e^{-4\kappa t})$	$\frac{1}{2}(1 + \cos 2\nu \cos \theta e^{-8\kappa t})$

Table I: Basic Quantities in Tripartite Teleportation

The probabilities P_m 's and q_{mn} 's in the noisy channels can be directly computed by changing ρ_{GHZ} into the mixed states (2.19) in Eq.(2.6) and Eq.(2.12). The results for the

$(L_{2,x}, L_{3,x}, L_{4,x})$, $(L_{2,y}, L_{3,y}, L_{4,y})$, $(L_{2,z}, L_{3,z}, L_{4,z})$ ¹, and isotropy noise channels are summarized in Table I. As Table I indicated, P_m 's and q_{mn} 's in the various noisy channels reduce to $P_i = 1/4 (i = 1, \dots, 4)$ and Eq.(2.14) when $\kappa = 0$ limit.

III. FIDELITIES

Type of noise	$F_C(\theta, \phi)$	$\bar{F}_C$
no noise	$1 - \frac{1}{2}(1 - \sin 2\nu) \sin^2 \theta$	$\frac{1}{3}(2 + \sin 2\nu)$
X noise	$\frac{1}{2}[(1 + \sin^2 \theta \cos^2 \phi \sin 2\nu) + e^{-4\kappa t}(\cos^2 \theta + \sin^2 \theta \sin^2 \phi \sin 2\nu)]$	$\frac{1}{6}[(3 + \sin 2\nu) + e^{-4\kappa t}(1 + \sin 2\nu)]$
Y noise	$\frac{1}{2}[1 + e^{-2\kappa t} \sin^2 \theta \sin^2 \phi \sin 2\nu + e^{-4\kappa t} \cos^2 \theta + e^{-6\kappa t} \sin^2 \theta \cos^2 \phi \sin 2\nu]$	$\frac{1}{6}[3 + e^{-2\kappa t} \sin 2\nu + e^{-4\kappa t} + e^{-6\kappa t} \sin 2\nu]$
Z noise	$1 - \frac{1}{2}(1 - \sin 2\nu e^{-6\kappa t}) \sin^2 \theta$	$\frac{1}{3}[2 + e^{-6\kappa t} \sin 2\nu]$
Isotropy noise	$\frac{1}{2}[1 + e^{-8\kappa t} \cos^2 \theta + e^{-12\kappa t} \sin^2 \theta \sin 2\nu]$	$\frac{1}{6}[3 + e^{-8\kappa t} + 2 \sin 2\nu e^{-12\kappa t}]$

Table II: Charlie's fidelity

The Charlie's fidelity, which measures how well the initial state ρ_{in} is transported to the Charlie's final state, can be computed as follows. Since Charlie's final state is τ_{mn} provided that Alice and Bob measure m and n respectively, one can define the fidelity F_{mn}^C in this case as a form

$$F_{mn}^C = \text{Tr} [\tau_{mn} \rho_{in}]. \quad (3.1)$$

Averaging over all possible measurement outcomes, we can define the Charlie's fidelity in a form

$$F_C(\theta, \phi) = \sum_{m=1}^4 \sum_{n=1}^2 P_m q_{mn} F_{mn}^C. \quad (3.2)$$

Finally, averaging $F_C(\theta, \phi)$ over all possible input states, we can define the Charlie's average fidelity $\bar{F}_C$ as follows:

$$\bar{F}_C = \frac{1}{4\pi} \int_0^\pi d\theta \int_0^{2\pi} d\phi \sin \theta F_C(\theta, \phi). \quad (3.3)$$

When there is no noise, $F_C(\theta, \phi)$ and $\bar{F}_C$ becomes

$$F_C(\theta, \phi) = 1 - \frac{1}{2}(1 - \sin 2\nu) \sin^2 \theta \quad \bar{F}_C = \frac{1}{3}(2 + \sin 2\nu). \quad (3.4)$$

¹ For simplicity, we will use the terminology X-, Y-, and Z-noises together for $(L_{2,x}, L_{3,x}, L_{4,x})$, $(L_{2,y}, L_{3,y}, L_{4,y})$, $(L_{2,z}, L_{3,z}, L_{4,z})$ noises

Thus, the Charlie's fidelities depend on the set of Bob's measurement operators. If Bob chooses $\nu = \pi/4$, $\bar{F}_C$ reaches to its maximum $\bar{F}_C = 1$, which means the perfect teleportation from Alice to Charlie.

The Charlie's fidelities $F_C(\theta, \phi)$ and $\bar{F}_C$ are summarized in Table II when the mixed states changed from $|GHZ\rangle$ by various noises are introduced as a quantum channel. Comparing Table II with Table I of Ref.[37], one can realize that the Charlie's fidelities with $\nu = \pi/4$ exactly coincide with fidelities of the bipartite teleportation when same noises are introduced initially in the quantum channel.

In the tripartite teleportation scheme, however, there are additional fidelities between Alice's state ρ_{in} and Bob's final state. Since Bob's final state after his measurement is N_1 or N_2 defined in Eq.(2.9) with respective probability $\sum_{i=1}^4 P_i q_{i1}$ or $\sum_{i=1}^4 P_i q_{i2}$, the Bob's final fidelities can be defined as

$$F_B^T(\theta, \phi) = \text{Tr}[N_1 \rho_{in}] \sum_{i=1}^4 P_i q_{i1} + \text{Tr}[N_2 \rho_{in}] \sum_{i=1}^4 P_i q_{i2} \quad (3.5)$$

$$\bar{F}_B^T = \frac{1}{4\pi} \int_0^\pi d\theta \int_0^{2\pi} d\phi \sin \theta F_B^T(\theta, \phi).$$

If one computes $F_B^T(\theta, \phi)$ and $\bar{F}_B^T$ for X-, Y-, Z-, and isotropy-noise channels, one can show that they are all same as

$$F_B^T(\theta, \phi) = \bar{F}_B^T = \frac{1}{2}. \quad (3.6)$$

This is too small because the optimal value for a classical teleportation scheme is 2/3.

Type of noise	Alice's outcome	$F_B^m(\theta, \phi)$	$\bar{F}_B^m$
X-noise and Y-noise	$m = 1, 2$	$\frac{1}{2} + \frac{1}{2} \cos 2\nu \cos 2\theta$ $\times (\cos 2\nu \cos \theta - \sin 2\nu \sin \theta) e^{-4\kappa t}$	$\frac{1}{6} (3 + e^{-4\kappa t} \cos^2 2\nu)$
	$m = 3, 4$	$\frac{1}{2} - \frac{1}{2} \cos 2\nu \cos 2\theta$ $\times (\cos 2\nu \cos \theta - \sin 2\nu \sin \theta) e^{-4\kappa t}$	$\frac{1}{6} (3 - e^{-4\kappa t} \cos^2 2\nu)$
no-noise and Z-noise	$m = 1, 2$	$\frac{1}{2} \left(1 + \cos^2 2\nu \cos^2 \theta \right.$ $\left. - \sin 2\nu \cos 2\nu \sin \theta \cos \theta \cos \phi \right)$	$\frac{2}{3} - \frac{1}{6} \sin^2 2\nu$
	$m = 3, 4$	$\frac{1}{2} \left(1 - \cos^2 2\nu \cos^2 \theta \right.$ $\left. + \sin 2\nu \cos 2\nu \sin \theta \cos \theta \cos \phi \right)$	$\frac{1}{3} + \frac{1}{6} \sin^2 2\nu$
Isotropy noise	$m = 1, 2$	$\frac{1}{2} + \frac{1}{2} \cos 2\nu \cos 2\theta$ $\times (\cos 2\nu \cos \theta - \sin 2\nu \sin \theta) e^{-8\kappa t}$	$\frac{1}{6} (3 + e^{-8\kappa t} \cos^2 2\nu)$
	$m = 3, 4$	$\frac{1}{2} - \frac{1}{2} \cos 2\nu \cos 2\theta$ $\times (\cos 2\nu \cos \theta - \sin 2\nu \sin \theta) e^{-8\kappa t}$	$\frac{1}{6} (3 - e^{-8\kappa t} \cos^2 2\nu)$

Table III: Bob's fidelities just after Alice broadcasts her outcome.

However, one can define the Bob's fidelities at the stage just after Alice broadcasts her measurement outcome to Bob and Charlie via classical channel. If Alice's outcome is m , then the Bob's fidelities can be defined as

$$\begin{aligned}
F_B^m(\theta, \phi) &= q_{m1} \text{Tr}[N_1 \rho_{in}] + q_{m2} \text{Tr}[N_2 \rho_{in}] \\
\bar{F}_B^m &= \frac{1}{4\pi} \int_0^\pi d\theta \int_0^{2\pi} d\phi \sin \theta F_B^m(\theta, \phi).
\end{aligned} \tag{3.7}$$

When there is no noise, it is straightforward to show that $F_B^m(\theta, \phi)$ and $\bar{F}_B^m$ become

$$\begin{aligned}
F_B^{m=1}(\theta, \phi) &= F_B^{m=2}(\theta, \phi) = \frac{1}{2} [1 + \cos^2 2\nu \cos^2 \theta - \sin 2\nu \cos 2\nu \sin \theta \cos \theta \cos \phi] \\
F_B^{m=3}(\theta, \phi) &= F_B^{m=4}(\theta, \phi) = \frac{1}{2} [1 - \cos^2 2\nu \cos^2 \theta + \sin 2\nu \cos 2\nu \sin \theta \cos \theta \cos \phi] \\
\bar{F}_B^{m=1} &= \bar{F}_B^{m=2} = \frac{2}{3} - \frac{1}{6} \sin^2 2\nu \\
\bar{F}_B^{m=3} &= \bar{F}_B^{m=4} = \frac{1}{3} + \frac{1}{6} \sin^2 2\nu.
\end{aligned} \tag{3.8}$$

When $m = 1$ or 2 , $\bar{F}_B^m$ reaches to its maximum value $2/3$ if $\nu = 0$ and $\nu = \pi/2$. At the same time the Charlie's fidelity $\bar{F}_C$ becomes to its minimum value $2/3$. When $\bar{F}_B^m$ reaches

to its minimum value $1/2$ at $\nu = \pi/4$, $\bar{F}_C$ becomes to its maximum value 1. Thus, one can increase/decrease $\bar{F}_B^m$ at the cost of decreasing/increasing $\bar{F}_C$.




FIG. 1: The ν - and κt -dependence of $\bar{F}_C$ and $\bar{F}_B^m$ with $m = 1, 2$ when the type of noise is $(L_{2,z}, L_{3,z}, L_{4,z})$. The upper and lower surfaces correspond to $\bar{F}_C$ and $\bar{F}_B^m$ respectively. The difference between $\bar{F}_C$ and $\bar{F}_B^m$ is maximized in the $\kappa t \rightarrow 0$ limit. However, this difference becomes negligible with increasing κt . This is due to the fact that decoherence is a major dominant effect in the region of large κt .

The Bob's fidelities $F_B^m(\theta, \phi)$ and $\bar{F}_B^m$ are summarized in Table III when the various noisy channels are introduced. One of the interesting points of Table III is that the Bob's fidelities for the Z-noisy channel is independent of the noise parameter κ while the Charlie's fidelities is dependent on κ as Table II indicated. The ν - and κt -dependence of $\bar{F}_C$ and $\bar{F}_B^m$ ($m = 1, 2$) in $(L_{2,z}, L_{3,z}, L_{4,z})$ noisy channel is plotted together in Fig. 1. The upper surface in the figure corresponds to $\bar{F}_C$ and the lower one to $\bar{F}_B^m$. The difference between $\bar{F}_C$ and $\bar{F}_B^m$ is averagely maximized when $\kappa = 0$, which means there is no noise. If, however, κt becomes larger and larger, the difference between two fidelities becomes negligible. This is due to the fact that the effect of noise is significant compared to the choice of ν in the Bob's measurement. One

can find a similar behaviors in the other noisy channels although we have not presented the ν - and κt -dependence of the fidelities explicitly in this paper.

IV. π -TANGLE

In this section we will compute the π -tangle of the various noisy channels defined in Eq.(1.11). When there is no noise, it is easy to show that

$$||\rho_{GHZ}^{T_A}|| = ||\rho_{GHZ}^{T_B}|| = ||\rho_{GHZ}^{T_C}|| = 2, \quad (4.1)$$

which results in

$$\mathcal{N}_{A(BC)} = \mathcal{N}_{B(AC)} = \mathcal{N}_{C(AB)} = 1. \quad (4.2)$$

In addition, one can show that there is no contribution to the entanglement from the two-tangles in GHZ state:

$$\mathcal{N}_{AB} = \mathcal{N}_{AC} = \mathcal{N}_{BC} = 0. \quad (4.3)$$

Thus, π -tangle for the GHZ state is simply

$$\pi_{ABC}^{GHZ} = 1, \quad (4.4)$$

which indicates that the GHZ state is a maximally entangled state.

Type of noise	π -tangle
no noise	1
X noise	$e^{-8\kappa t}$
Y noise	$\frac{1}{64} \left[1 - 3e^{-2\kappa t} - e^{-4\kappa t} - e^{-6\kappa t} - (1 - 3e^{-2\kappa t} - e^{-4\kappa t} - e^{-6\kappa t}) \right]^2$
Z noise	$e^{-12\kappa t}$
Isotropy	$\frac{1}{64} \left[1 - e^{-8\kappa t} - 4e^{-12\kappa t} - (1 - e^{-8\kappa t} - 4e^{-12\kappa t}) \right]^2$
noise	

Table IV: The π -tangles for the various noisy channels

The π -tangles for $(L_{2,x}, L_{3,x}, L_{4,x})$, $(L_{2,y}, L_{3,y}, L_{4,y})$, $(L_{2,z}, L_{3,z}, L_{4,z})$, and isotropy channels can be computed straightforwardly. For all noisy channels $\mathcal{N}_{A(BC)} = \mathcal{N}_{B(AC)} = \mathcal{N}_{C(AB)}$ and

$\mathcal{N}_{AB} = \mathcal{N}_{AC} = \mathcal{N}_{BC} = 0$ hold. This seems to be due to the fact that we considered only same-axis noisy channels. The π -tangles for the various noisy channels are summarized at Table IV. The interesting fact Table IV indicates is that while the π -tangles for the X- and Z-noise channels vanish at $\kappa t \rightarrow \infty$ limit, those for the Y- and isotropy-noise channels goes to zero at $y_* \leq \kappa t \leq \infty$ and $i_* \leq \kappa t \leq \infty$ respectively, where

$$y_* = \ln \frac{1 + (19 + 3\sqrt{33})^{1/3} + (19 - 3\sqrt{33})^{1/3}}{3} \sim 0.609378 \quad (4.5)$$

$$i_* = \frac{1}{4} \ln \frac{(54 + 3\sqrt{321})^{1/3} + (54 - 3\sqrt{321})^{1/3}}{3} \sim 0.146435.$$




FIG. 2: The κt dependence of π -tangles and Charlie's average fidelities $\bar{F}_C$ in $(L_{2,x}, L_{3,x}, L_{4,x})$ (Fig. 2a), $(L_{2,y}, L_{3,y}, L_{4,y})$ (Fig. 2b), $(L_{2,z}, L_{3,z}, L_{4,z})$ (Fig. 2c), and isotropy (Fig. 2d) noisy channels.

The κt -dependence of π -tangles together with Charlie's average fidelity $\bar{F}_C$ for the various noisy channels are plotted in Fig. 2. In the Z-noisy channel the π -tangle vanishes at $\kappa t = \infty$

and at this limit $\bar{F}_C$ goes to $2/3$ regardless of ν , which is a classical fidelity limit. In the X-noise channel $\bar{F}_C$ goes to $(3 + \sin 2\nu)/6$ at $\kappa t = \infty$. When $\nu = \pi/4$, this also goes to $2/3$. Therefore, the π -tangles for X- and Z-noise channels seem to show a nice connection between the Charlie's average fidelity and three-way entanglement of the given channel.

However, this nice property is not maintained in the Y- and isotropy-noise channel. In the Y-noise channel the π -tangle vanishes at $y_* \leq \kappa t$. At $\kappa t = y_*$ the Charlie fidelity reduces to $0.166667(3.08738 + 0.321426 \sin 2\nu)$, whose maximum is $f_Y = 0.568314$. Thus f_Y is much less than the classical fidelity limit $2/3$. Similar behavior can be found in the isotropy channel. In this channel the π -tangle vanishes at $i_* \leq \kappa t$. At $\kappa t = i_*$ the maximum Charlie's fidelity becomes $f_I = 0.609159$, which is also less than the classical limit $2/3$.

V. THREE-TANGLE

In this section we would like to discuss the three-tangles for the various noisy channels expressed in Eq.(2.19).

A. $(L_{2,z}, L_{3,z}, L_{4,z})$ noisy channel

Let us consider the pure state

$$|Z(z, \varphi)\rangle = \sqrt{z}|GHZ, 1\rangle - e^{i\varphi}\sqrt{1-z}|GHZ, 2\rangle \quad (5.1)$$

where $z = (1 + e^{-6\kappa t})/2$. It is easy to show that the three-tangle of $|Z(z, \varphi)\rangle$ is

$$\tau_3(|Z(z, \varphi)\rangle) = (1 - 2z + 2z^2) - 2z(1 - z) \cos 2\varphi. \quad (5.2)$$

Thus, $\tau_3(|Z(z, \varphi)\rangle)$ has a minimum at $\varphi = 0$ and $\varphi = \pi$, i.e.

$$\tau_3(|Z(z, 0)\rangle) = \tau_3(|Z(z, \pi)\rangle) = (1 - 2z)^2. \quad (5.3)$$

In terms of the terminologies of Ref.[38] $(1 - 2z)^2$ forms a convex characteristic curve in $(z, \tau_3(|Z(z, \varphi)\rangle))$ plane. In addition, one can show straightforwardly that $\varepsilon(\rho_{GHZ})$ defined in Eq.(2.19) can be decomposed into

$$\varepsilon(\rho_{GHZ}) = \frac{1}{2}|Z(z, 0)\rangle\langle Z(z, 0)| + \frac{1}{2}|Z(z, \pi)\rangle\langle Z(z, \pi)|. \quad (5.4)$$

If Eq.(5.4) is optimal, then the three-tangle for $\varepsilon(\rho_{GHZ})$ is $(2z - 1)^2$. Since this coincides with the convex characteristic curve, Eq.(5.4) should be the optimal decomposition. Thus, the three-tangle for the $\varepsilon(\rho_{GHZ})$ is

$$\tau_{ABC}^z = (1 - 2z)^2 = e^{-12\kappa t}. \quad (5.5)$$

It is interesting to note that the three-tangle and π -tangle are same with each other in this channel.

B. $(L_{2,x}, L_{3,x}, L_{4,x})$ noisy channel

Before we start computation, it is worthwhile noting that as shown in Ref.[20] the state

$$\Pi_{GHZ} = \frac{1}{3} \left[|GHZ, 3\rangle\langle GHZ, 3| + |GHZ, 5\rangle\langle GHZ, 5| + |GHZ, 7\rangle\langle GHZ, 7| \right] \quad (5.6)$$

has vanishing three-tangle. This fact is shown in appendix A.

Now, let us consider a pure state

$$\begin{aligned} |X(x, \varphi_1, \varphi_2, \varphi_3)\rangle &= \sqrt{x}|GHZ, 1\rangle - e^{i\varphi_1} \sqrt{\frac{1-x}{3}}|GHZ, 3\rangle \\ &\quad - e^{i\varphi_2} \sqrt{\frac{1-x}{3}}|GHZ, 5\rangle - e^{i\varphi_3} \sqrt{\frac{1-x}{3}}|GHZ, 7\rangle \end{aligned} \quad (5.7)$$

where $x = (1 + 3e^{-4\kappa t})/4$. Then it is easy to show that the three-tangle of $|X(x, \varphi_1, \varphi_2, \varphi_3)\rangle$ becomes

$$\begin{aligned} \tau_3(|X(x, \varphi_1, \varphi_2, \varphi_3)\rangle) &= \left| x^2 + \frac{(1-x)^2}{9} (e^{4i\varphi_1} + e^{4i\varphi_2} + e^{4i\varphi_3}) - \frac{2}{3}x(1-x) (e^{2i\varphi_1} + e^{2i\varphi_2} + e^{2i\varphi_3}) \right. \\ &\quad \left. - \frac{2}{9}(1-x)^2 (e^{2i(\varphi_1+\varphi_2)} + e^{2i(\varphi_1+\varphi_3)} + e^{2i(\varphi_2+\varphi_3)}) - \frac{8\sqrt{3}}{9} \sqrt{x(1-x)^3} e^{i(\varphi_1+\varphi_2+\varphi_3)} \right|. \end{aligned} \quad (5.8)$$

The vectors $|X(x, \varphi_1, \varphi_2, \varphi_3)\rangle$ has following properties. The three-tangle of it has the largest zero at $x = x_0 \equiv 3/4$ and $\varphi_1 = \varphi_2 = \varphi_3 = 0$. The vectors $|X(x, 0, 0, 0)\rangle$, $|X(x, 0, \pi, \pi)\rangle$, $|X(x, \pi, 0, \pi)\rangle$ and $|X(x, \pi, \pi, 0)\rangle$ have same three-tangles. Finally, $\varepsilon_X(\rho_{GHZ})$ can be decomposed into

$$\begin{aligned} \varepsilon_X(\rho_{GHZ}) &= \frac{1}{4} \left[|X(x, 0, 0, 0)\rangle\langle X(x, 0, 0, 0)| + |X(x, 0, \pi, \pi)\rangle\langle X(x, 0, \pi, \pi)| \right. \\ &\quad \left. + |X(x, \pi, 0, \pi)\rangle\langle X(x, \pi, 0, \pi)| + |X(x, \pi, \pi, 0)\rangle\langle X(x, \pi, \pi, 0)| \right]. \end{aligned} \quad (5.9)$$

When $x \leq x_0$, one can construct the optimal decomposition in the following form:

$$\begin{aligned} \varepsilon_X(\rho_{GHZ}) = & \frac{x}{4x_0} \left[|X(x_0, 0, 0, 0)\rangle\langle X(x_0, 0, 0, 0)| + |X(x_0, 0, \pi, \pi)\rangle\langle X(x_0, 0, \pi, \pi)| \right. \\ & \left. + |X(x_0, \pi, 0, \pi)\rangle\langle X(x_0, \pi, 0, \pi)| + |X(x_0, \pi, \pi, 0)\rangle\langle X(x_0, \pi, \pi, 0)| \right] \\ & + \frac{x_0 - x}{x_0} \Pi_{GHZ}. \end{aligned} \quad (5.10)$$

Since Π_{GHZ} has the vanishing three-tangle, one can show easily

$$\tau_{ABC}^X = 0 \quad \text{when } x \leq x_0 = 3/4. \quad (5.11)$$

Now, let us consider the three-tangle of $\varepsilon_X(\rho_{GHZ})$ in the region $x_0 \leq x \leq 1$. Since Eq.(5.9) is an optimal decomposition at $x = x_0$, one can conjecture that it is also optimal in the region $x_0 \leq x$. As will be shown shortly, however, this is not true at the large- x region. If we compute the three-tangle under the condition that Eq.(5.9) is optimal at $x_0 \leq x$, its expression becomes

$$\alpha_I^X(x) = x^2 - \frac{1}{3}(1-x)^2 - 2x(1-x) - \frac{8\sqrt{3}}{9}\sqrt{x(1-x)^3}. \quad (5.12)$$

However, one can show straightforwardly that $\alpha_I^X(x)$ is not a convex function in the region $x \geq x_*$, where

$$x_* = \frac{1}{4} (1 + 2^{1/3} + 4^{1/3}) \approx 0.961831. \quad (5.13)$$

Therefore, we need to convexify $\alpha_I^X(x)$ in the region $x_1 \leq x \leq 1$ to make the three-tangle to be convex function, where x_1 is some number between x_0 and x_* . The number x_1 will be determined shortly.

In the large x -region one can derive the optimal decomposition in a form:

$$\begin{aligned} \varepsilon_X(\rho_{GHZ}) &= \frac{1-x}{4(1-x_1)} \left[|X(x_1, 0, 0, 0)\rangle\langle X(x_1, 0, 0, 0)| + |X(x_1, 0, \pi, \pi)\rangle\langle X(x_1, 0, \pi, \pi)| \right. \\ &\quad \left. + |X(x_1, \pi, 0, \pi)\rangle\langle X(x_1, \pi, 0, \pi)| + |X(x_1, \pi, \pi, 0)\rangle\langle X(x_1, \pi, \pi, 0)| \right] \\ &\quad + \frac{x-x_1}{1-x_1} |GHZ, 1\rangle\langle GHZ, 1| \end{aligned} \quad (5.14)$$

which gives a three-tangle as

$$\alpha_{II}^X(x, x_1) = \frac{1-x}{1-x_1} \alpha_I^X(x_1) + \frac{x-x_1}{1-x_1}. \quad (5.15)$$

Since $d^2\alpha_{II}^X/dx^2 = 0$, there is no convex problem if $\alpha_{II}^X(x, x_1)$ is a three-tangle in the large- x region. The constant x_1 can be fixed from the condition of minimum α_{II}^X , i.e. $\partial\alpha_{II}^X(x, x_1)/\partial x_1 = 0$, which gives

$$x_1 = \frac{1}{4}(2 + \sqrt{3}) \approx 0.933013. \quad (5.16)$$

As expected x_1 is between x_0 and x_* . Thus, finally the three-tangle for $\varepsilon_X(\rho_{GHZ})$ becomes

$$\tau_{ABC}^X = \begin{cases} 0 & x \leq x_0 \\ \alpha_I^X(x) & x_0 \leq x \leq x_1 \\ \alpha_{II}^X(x, x_1) & x_1 \leq x \leq 1 \end{cases} \quad (5.17)$$

and the corresponding optimal decompositions are Eq.(5.10), Eq.(5.9) and Eq.(5.14) respectively. In terms of κt τ_{ABC}^X reduces to

$$\tau_{ABC}^X = \begin{cases} \alpha_{II}^X(x, x_1) & 0 \leq \kappa t \leq \mu_1^X \\ \alpha_I^X(x) & \mu_1^X \leq \kappa t \leq \mu_2^X \\ 0 & \mu_2^X \leq \kappa t \leq \infty \end{cases} \quad (5.18)$$

where $x = (1 + 3e^{-4\kappa t})/3$ and

$$\mu_1^X = -\frac{1}{4} \ln \frac{4x_1 - 1}{3} \approx 0.0233899 \quad \mu_2^X = -\frac{1}{4} \ln \frac{2}{3} \approx 0.101366. \quad (5.19)$$

C. $(L_{2,y}, L_{3,y}, L_{4,y})$ noisy channel

The mixed state $\varepsilon_Y(\rho_{GHZ})$ given in Eq.(2.19) can be re-written as

$$\varepsilon_Y(\rho_{GHZ}) = \xi \Pi_1^{GHZ}(Y_1) + (1 - \xi) \Pi_2^{GHZ}(Y_2) \quad (5.20)$$

where

$$\begin{aligned} \Pi_1^{GHZ}(Y_1) &= Y_1 |GHZ, 1\rangle \langle GHZ, 1| \\ &\quad + \frac{1 - Y_1}{3} \left[|GHZ, 3\rangle \langle GHZ, 3| + |GHZ, 5\rangle \langle GHZ, 5| + |GHZ, 7\rangle \langle GHZ, 7| \right] \\ \Pi_2^{GHZ}(Y_2) &= Y_2 |GHZ, 2\rangle \langle GHZ, 2| \\ &\quad + \frac{1 - Y_2}{3} \left[|GHZ, 4\rangle \langle GHZ, 4| + |GHZ, 6\rangle \langle GHZ, 6| + |GHZ, 8\rangle \langle GHZ, 8| \right]. \end{aligned} \quad (5.21)$$

In Eq.(5.21) the constants are given by

$$\xi = \frac{y_+(y_+^2 + 3y_-^2)}{8} \quad Y_1 = \frac{y_+^2}{y_+^2 + 3y_-^2} \quad Y_2 = \frac{y_-^2}{3y_+^2 + y_-^2} \quad (5.22)$$

where $y_{\pm} = 1 \pm e^{-2\kappa t}$. It is worthwhile noting that $\Pi_2^{GHZ}(Y_2)$ is local-unitary (LU) equivalent to $\Pi_1^{GHZ}(Y_2)$, i.e.

$$\Pi_1^{GHZ}(Y_2) = (\sigma_z \otimes \mathbb{1} \otimes \mathbb{1}) \Pi_2^{GHZ}(Y_2) (\sigma_z \otimes \mathbb{1} \otimes \mathbb{1})^\dagger.$$

Since the three-tangle is LU-invariant quantity, the three-tangle for $\Pi_2^{GHZ}(Y_2)$ should be equal to that for $\Pi_1^{GHZ}(Y_2)$. Since $\Pi_1^{GHZ}(Y_2)$ can be obtained from $\varepsilon_X(\rho_{GHZ})$ by replacing x by Y_2 , one can compute the three-tangle for $\Pi_2^{GHZ}(Y_2)$ directly from Eq.(5.17). Since, furthermore, $Y_2 \leq 1/4$ in the entire range of κt , the three-tangle for $\Pi_2^{GHZ}(Y_2)$ should be zero.

Since $\varepsilon_Y(\rho_{GHZ})$ is rank-8 mixed state, it seems to be highly difficult to compute the three-tangle. Still we do not know how to compute it analytically. However, one can compute its upper bound as following. Since the three-tangle for $\Pi_2^{GHZ}(Y_2)$ is zero and the three-tangle for the mixed state is obtained by the convex-roof method, Eq.(5.20) implies that the three-tangle for $\varepsilon_Y(\rho_{GHZ})$ should be less than ξ times three-tangle for $\Pi_1^{GHZ}(Y_1)$. Since $\Pi_1^{GHZ}(Y_1)$ is same with $\varepsilon_X(\rho_{GHZ})$ if x is replaced by Y_1 , one can compute the upper bound of the three-tangle for $\varepsilon_Y(\rho_{GHZ})$, $\tau_{ABC}^{Y:UB}$ directly from Eq.(5.17). The superscript UB stands for upper bound. The final result of this upper bound can be summarized as

$$\tau_{ABC}^{Y:UB} = \begin{cases} \xi \alpha_I^X(Y_1, x_1) & 0 \leq \kappa t \leq \nu_1^* \\ \xi \alpha_I^X(Y_1) & \nu_1^* \leq \kappa t \leq \nu_2^* \\ 0 & \nu_2^* \leq \kappa t \leq \infty \end{cases} \quad (5.23)$$

where

$$\nu_1^* = -\frac{1}{2} \ln(\sqrt{3} - 1) \sim 0.155953 \quad \nu_2^* = \frac{1}{2} \ln 2 \sim 0.346574. \quad (5.24)$$

Of course, x_1 is given in Eq.(5.16).

D. isotropy noisy channel

The mixed state $\varepsilon_I(\rho_{GHZ})$ given in Eq.(2.19) can be re-written as

$$\varepsilon_I(\rho_{GHZ}) = \zeta \Sigma_1^{GHZ} + (1 - \zeta) \Sigma_2^{GHZ} \quad (5.25)$$

where

$$\begin{aligned}\Sigma_1^{GHZ} &= \left(\frac{1}{2} + \frac{2p^3}{1+3p^2}\right) |GHZ, 1\rangle\langle GHZ, 1| \\ &\quad + \left(\frac{1}{2} - \frac{2p^3}{1+3p^2}\right) |GHZ, 2\rangle\langle GHZ, 2| \\ \Sigma_2^{GHZ} &= \frac{1}{6} \{I - (|000\rangle\langle 000| + |111\rangle\langle 111|)\}\end{aligned}\tag{5.26}$$

and

$$\zeta = \frac{1+3p^2}{4}\tag{5.27}$$

with $p = e^{-4\kappa t}$.

The state $\varepsilon_I(\rho_{GHZ})$ is rank-8 mixed state and we do not know how to compute the three-tangle of it exactly. Since, however, the three-tangle of Σ_2^{GHZ} is zero, one can compute at least the upper bound as ζ times three-tangle of Σ_1^{GHZ} . This upper bound can be easily computed by making use of the analytical result of the three-tangle for the Z-noise channel. The final result of this upper bound is

$$\tau_{ABC}^{I:UB} = \frac{4p^6}{1+3p^2} = \frac{4e^{-24\kappa t}}{1+3e^{-8\kappa t}}\tag{5.28}$$

where the superscript UB stands for the upper bound.

VI. CONCLUSION

In this paper we computed the π -tangles explicitly for the mixed states summarized in Eq.(2.19). It is shown that the π -tangles for the X- and Z-noisy channels vanish at $\kappa t \rightarrow \infty$, where the maximum Charlie's fidelities reduce to the classical limit $2/3$. However, this nice property is not maintained for Y- and isotropy-noise channels. For Y-noise the π -tangle vanishes at $y_* \leq \kappa t$, where y_* is given at Eq.(4.5). At $\kappa t = y_*$ the maximum Charlie's fidelity becomes 0.57, which is much less than the classical limit. For isotropy noise the π -tangle vanishes at $i_* \leq \kappa t$. At $\kappa t = i_*$ the maximum Charlie's fidelity becomes 0.61, which is also less than the classical limit. Although the π -tangle was constructed in Ref.[21] to reflect the three-party entanglement of the W-type states, it does not seem to give a meaningful interpretation in the real quantum information process.

We also computed the three-tangles for the X- and Z-noise channels. The remarkable fact is that the three-tangle for the Z-noise channel is exactly same with the corresponding




FIG. 3: The κt dependence of three-tangle and π -tangle for $(L_{2,x}, L_{3,x}, L_{4,x})$ (Fig. 3a), $(L_{2,y}, L_{3,y}, L_{4,y})$ (Fig. 3b), and isotropy (Fig. 3c) noisy channels.

π -tangle. Therefore, the three-tangle for the Z-noise channel vanishes at $\kappa t \rightarrow \infty$, where all Charlie's fidelities reduce to the classical limit regardless of Bob's measurement outcome. For X-noise the κt -dependence of the three tangle is plotted in Fig. 3(a). For comparison we plotted the corresponding π -tangle together. As Fig. 3(a) has shown, the three-tangle is much less than the corresponding π -tangle. In this channel the three-tangle vanishes at $\mu_2^X \leq \kappa t$, where $\mu_2^X = -(1/4) \ln(2/3)$. At $\kappa t = \mu_2^X$ the Charlie's fidelity becomes $(11 + 5 \sin 2\nu)/18$. When, therefore, $\nu = (1/2) \sin^{-1}(1/5) \sim 0.100679$, Charlie's fidelity reduces to the classical limit $2/3$. However, the maximum Charlie's fidelity goes to $8/9$, which is much larger than the classical limit.

The κt -dependence of $\tau_{ABC}^{Y:UB}$ and $\tau_{ABC}^{I:UB}$ are plotted in Fig. 3(b) and Fig. 3(c) respectively. For comparison we plotted the corresponding π -tangle together. Fig. 3(b) shows that $\tau_{ABC}^{Y:UB}$

is larger than the corresponding π -tangle at $0 \leq \kappa t \leq 0.315$. Fig. 3(c) shows that $\tau_{ABC}^{I:UB}$ is larger than the corresponding π -tangle in the entire range of κt . This is due to the fact that $\tau_{ABC}^{Y:UB}$ and $\tau_{ABC}^{I:UB}$ are merely the upper bounds of the real three-tangles for Y- and isotropy-noise channels. If the calculational tool for the three-tangle of the arbitrary three-party mixed states are developed someday, the real three-tangles computed via this tool should be less than the corresponding π -tangles.

In this paper we examined the physical meaning of the three-tangle and π -tangle in the real quantum information process. We adopted the three-party teleportation via various noisy channels as a model of quantum process. It is shown that the π -tangle seems to be too large to have a meaningful interpretation. Although we cannot compute the three-tangles for Y- and isotropy-noise channels due to their high rank, the results for X- and Z-noise seems to imply the fact that the three-tangle is too small to have meaningful interpretation. Probably we need a different three-party entanglement measure whose value is between three-tangle and π -tangle.

Acknowledgement: This work was supported by the Kyungnam University Foundation Grant, 2008.

-
- [1] M. A. Nielsen and I. L. Chuang, *Quantum Computation and Quantum Information* (Cambridge University Press, Cambridge, England, 2000).
 - [2] C. H. Bennett, G. Brassard, C. Crépeau, R. Jozsa, A. Peres and W. K. Wootters, *Teleporting an Unknown Quantum State via Dual Classical and Einstein-Podolsky-Rosen Channles*, Phys. Rev. Lett. **70** (1993) 1895.
 - [3] C. H. Bennett and S. J. Wiesner, *Communication vi one- and two-particle operators on Einstein-Podolsky-Rosen states*, Phys. Rev. Lett. **69** (1992) 2881.
 - [4] G. Vidal, *Efficient classical simulation of slightly entangled quantum computations*, Phys. Rev. Lett. **91** (2003) 147902 [quant-ph/0301063].
 - [5] T. C. Wei and P. M. Goldbart, *Geometric measure of entanglement and applications to bipartite and multipartite quantum states*, Phys. Rev. **A68** (2003) 042307 [quant-ph/0307219];
E. Jung, M. R. Hwang, H. Kim, M. S. Kim, D. K. Park, J. W. Son and S. Tamaryan, *Reduced State Uniquely Defines Groverian Measure of Original Pure State*, Phys. Rev. **A77**

- (2008) 062317 [arXiv:0709.4292 (quant-ph)]; L. Tamaryan, D. K. Park and S. Tamaryan, *Analytic Expressions for Geometric Measure of Three Qubit States*, Phys. Rev. **A 77** (2008) 022325, [arXiv:0710.0571 (quant-ph)]; L. Tamaryan, D. K. Park, J. W. Son, S. Tamaryan, *Geometric Measure of Entanglement and Shared Quantum States*, Phys. Rev. **A78** (2008) 032304, [arXiv:0803.1040 (quant-ph)]; E. Jung, M. R. Hwang, D. K. Park, L. Tamaryan and S. Tamaryan, *Three-Qubit Groverian Measure*, Quant. Inf. Comp. **8** (2008) 0925 [arXiv:0803.3311 (quant-ph)]; L. Tamaryan, H. Kim, E. Jung, M. R. Hwang, D. K. Park and S. Tamaryan, *Toward an understanding of entanglement for generalized n -qubit W -state*, arXiv:0806.1314 (quant-ph); L. Tamaryan, D. K. Park and S. Tamaryan, *Generalized Schmidt Decomposition based on Injective Tensor Norm*, arXiv:0809.1290 (quant-ph).
- [6] C. H. Bennett, D. P. DiVincenzo, J. A. Smolin and W. K. Wootters, *Mixed-state entanglement and quantum error correction*, Phys. Rev. **A54** (1996) 3824 [quant-ph/9604024].
- [7] A. Uhlmann, *Fidelity and concurrence of conjugate states*, Phys. Rev. **A 62** (2000) 032307 [quant-ph/9909060].
- [8] S. Hill and W. K. Wootters, *Entanglement of a Pair of Quantum Bits*, Phys. Rev. Lett. **78** (1997) 5022 [quant-ph/9703041].
- [9] W. K. Wootters, *Entanglement of Formation of an Arbitrary State of Two Qubits*, Phys. Rev. Lett. **80** (1998) 2245 [quant-ph/9709029].
- [10] V. Coffman, J. Kundu and W. K. Wootters, *Distributed entanglement*, Phys. Rev. **A61** (2000) 052306 [quant-ph/9907047].
- [11] A. Cayley, *On the Theory of Linear Transformations*, Cambridge Math. J. **4** (1845) 193.
- [12] A. Miyake, *Classification of multipartite entangled states by multidimensional determinants*, Phys. Rev. **A67** (2003) 012108 [quant-ph/0206111].
- [13] F. Verstraete, J. Dehaene and B. D. Moor, *Normal forms and entanglement measures for multipartite quantum states*, Phys. Rev. **A68** (2003) 012103 [quant-ph/0105090].
- [14] M. S. Leifer, N. Linden and A. Winter, *Measuring polynomial invariants of multiparty quantum states*, Phys. Rev. **A69** (2004) 052304 [quant-ph/0308008].
- [15] D. M. Greenberger, M. Horne, and A. Zeilinger, *Bell's Theorem, Quantum Theory, and Conceptions of the Universe*, edited by M. Kafatos (Kluwer, Dordrecht, 1989) p 69.
- [16] W. Dür, G. Vidal, and J. I. Cirac, *Three qubits can be entangled in two inequivalent ways*, Phys. Rev. **A62** (2000) 062314 [quant-ph/0005115].

- [17] R. Lohmayer, A. Osterloh, J. Siewert and A. Uhlmann, *Entangled Three-Qubit States without Concurrence and Three-Tangle*, Phys. Rev. Lett. **97** (2006) 260502 [quant-ph/0606071].
- [18] C. Eltschka, A. Osterloh, J. Siewert and A. Uhlmann, *Three-tangle for mixtures of generalized GHZ and generalized W states*, New J. Phys. **10** (2008) 043014, arXiv:0711.4477 (quant-ph).
- [19] E. Jung, M. R. Hwang, D. K. Park and J. W. Son, *Three-tangle for Rank-3 Mixed States: Mixture of Greenberger-Horne-Zeilinger, W and flipped W states*, Phys. Rev. **A79** (2009) 024306, arXiv:0810.5403 (quant-ph).
- [20] E. Jung, D. K. Park, and J. W. Son, *Does three-tangle properly quantify the three-party entanglement for Greenberger-Horne-Zeilinger-type state?*, arXiv:0901.2610 (quant-ph).
- [21] Y. U. Ou and H. Fan, *Monogamy Inequality in terms of Negativity for Three-Qubit States*, Phys. Rev. **A75** (2007) 062308 [quant-ph/0702127].
- [22] G. Vidal and R. F. Werner, *Computable measure of entanglement*, Phys. Rev. **A65** (2002) 032314 [quant-ph/0102117].
- [23] A. Peres, *Separability Criterion for Density Matrices*, Phys. Rev. Lett. **77** (1996) 1413 [quant-ph/9604005].
- [24] M. Horodecki, P. Horodecki and R. Horodecki, *Separability of mixed states: necessary and sufficient conditions*, Phys. Lett. **A 223** (1996) 1 [quant-ph/9605038].
- [25] P. Horodecki, *Separability criterion and inseparable mixed states with partial transposition*, Phys. Lett. **A 232** (1997) 333 [quant-ph/9703004]
- [26] A. Karlsson and M. Bourennane, *Quantum teleportation using three-particle entanglement*, Phys. Rev. **A58** (1998) 4394.
- [27] E. Jung, M. R. Hwang, D. K. Park, J. W. Son and S. Tamaryan, *Mixed-state entanglement and quantum teleportation through noisy channels*, J. Phys. A: Math. Theor. **41** (2008) 385302 [arXiv:0804.4595 (quant-ph)].
- [28] S. Popescu, *Bell's Inequalities versus Teleportation: What is Nonlocality*, Phys. Rev. Lett. **72** (1994) 797.
- [29] Y. Yeo, *Quantum teleportation using three-particle entanglement*, quant-ph/0302030.
- [30] W. K. Wootters and W. H. Zurek, *A single quantum cannot be cloned*, Nature, **299** (1982) 802.
- [31] H. Barnum, C. M. Caves, C. A. Fuchs, R. Jozsa and B. Schumacher, *Noncommuting Mixed States Cannot Be Broadcast*, Phys. Rev. Lett. **76** (1996) 2818 [quant-ph/9511010].

- [32] V. Buzek and M. Hillery, *Quantum copying: Beyond the no-cloning theorem*, Phys. Rev. **A54** (1996) 1844 [quant-ph/9607018].
- [33] V. Buzek, V. Vedral, M. B. Plenio, P. L. Knight, and M. Hillery, *Broadcasting of entanglement via local copying*, Phys. Rev. **A55** (1997) 3327 [quant-ph/9701028].
- [34] V. Buzek, S. L. Braunstein, M. Hillery, and D. Bruss, *Quantum copying: A network*, quant-ph/9703046.
- [35] N. Gisin and S. Massar, *Optimal Quantum Cloning Machines*, Phys. Rev. Lett. **79** (1997) 2153 [quant-ph/9705046].
- [36] G. Lindblad, *On the generators of quantum dynamical semigroups*, Commun. Math. Phys. **48** (1976) 119.
- [37] Eylee Jung, Mi-Ra Hwang, You-Hwan Ju, Min-Soo Kim, Sahng-Kyoon Yoo, Hungsoo Kim, DaeKil Park, Jin-Woo Son, S. Tamaryan, and Seong-Keuck Cha, *Greenberger-Horne-Zeilinger versus W: Quantum Teleportation through Noisy Channels*, Phys. Rev. **A78** (2008) 012312 [arXiv:0801.1433 (quant-ph)].
- [38] A. Osterloh, J. Siewert and A. Uhlmann, *Tangles of superpositions and the convex-roof extension*, Phys. Rev. **A77** (2008) 032310, arXiv:0710.5909 (quant-ph).

Appendix A

In this appendix we would like to prove that Π_{GHZ} defined in Eq.(5.6) has vanishing three-tangle. Consider a pure state

$$|J(\theta_1, \theta_2)\rangle = \frac{1}{\sqrt{3}}|GHZ, 3\rangle - \frac{1}{\sqrt{3}}e^{i\theta_1}|GHZ, 5\rangle - \frac{1}{\sqrt{3}}e^{i\theta_2}|GHZ, 7\rangle. \quad (\text{A.1})$$

Then, it is easy to show that the three-tangle of $|J(\theta_1, \theta_2)\rangle$ is

$$\tau_3(\theta_1, \theta_2) = \frac{1}{9}|1 - (e^{i\theta_1} - e^{i\theta_2})^2| |1 - (e^{i\theta_1} + e^{i\theta_2})^2|, \quad (\text{A.2})$$

which vanishes when

$$\begin{aligned} (i) \quad & e^{i\theta_1} - e^{i\theta_2} = 1 \implies (\theta_1 = \pi/3, \theta_2 = 2\pi/3), (\theta_1 = 5\pi/3, \theta_2 = 4\pi/3) \\ (ii) \quad & e^{i\theta_1} - e^{i\theta_2} = -1 \implies (\theta_1 = 2\pi/3, \theta_2 = \pi/3), (\theta_1 = 4\pi/3, \theta_2 = 5\pi/3) \\ (iii) \quad & e^{i\theta_1} + e^{i\theta_2} = 1 \implies (\theta_1 = \pi/3, \theta_2 = 5\pi/3), (\theta_1 = 5\pi/3, \theta_2 = \pi/3) \\ (iv) \quad & e^{i\theta_1} + e^{i\theta_2} = -1 \implies (\theta_1 = 2\pi/3, \theta_2 = 4\pi/3), (\theta_1 = 4\pi/3, \theta_2 = 2\pi/3). \end{aligned} \quad (\text{A.3})$$

Furthermore, one can show straightforwardly that Π_{GHZ} can be decomposed into

$$\begin{aligned} \Pi_{GHZ} = \frac{1}{8} & \left[|J\left(\frac{\pi}{3}, \frac{2\pi}{3}\right)\rangle \langle J\left(\frac{\pi}{3}, \frac{2\pi}{3}\right)| + |J\left(\frac{\pi}{3}, \frac{5\pi}{3}\right)\rangle \langle J\left(\frac{\pi}{3}, \frac{5\pi}{3}\right)| \right. \\ & + |J\left(\frac{2\pi}{3}, \frac{\pi}{3}\right)\rangle \langle J\left(\frac{2\pi}{3}, \frac{\pi}{3}\right)| + |J\left(\frac{2\pi}{3}, \frac{4\pi}{3}\right)\rangle \langle J\left(\frac{2\pi}{3}, \frac{4\pi}{3}\right)| \\ & + |J\left(\frac{4\pi}{3}, \frac{2\pi}{3}\right)\rangle \langle J\left(\frac{4\pi}{3}, \frac{2\pi}{3}\right)| + |J\left(\frac{4\pi}{3}, \frac{5\pi}{3}\right)\rangle \langle J\left(\frac{4\pi}{3}, \frac{5\pi}{3}\right)| \\ & \left. + |J\left(\frac{5\pi}{3}, \frac{\pi}{3}\right)\rangle \langle J\left(\frac{5\pi}{3}, \frac{\pi}{3}\right)| + |J\left(\frac{5\pi}{3}, \frac{4\pi}{3}\right)\rangle \langle J\left(\frac{5\pi}{3}, \frac{4\pi}{3}\right)| \right]. \end{aligned} \quad (\text{A.4})$$

Combining Eq.(A.3) and (A.4), one can show that Eq.(A.4) is the optimal decomposition of Π_{GHZ} and the three-tangle is

$$\tau_3(\Pi_{GHZ}) = 0. \quad (\text{A.5})$$